

Hektor separates milled PCBs carefully and fast. The off-cut material is removed smoothly and precisely. The matrix consists of two parts. This ensures easy and cost-saving change of the blades. Compressed air is used for the separation process. The operating pressure can be set on the machine. When the foot switch is pressed, the off-cut is punched out. The off-cuts are collected in the collecting box. When the gate is opened the waste material can be extracted.

																																														Part No.	Description	
																												Part No Description	Part No Description	Part No Description	Part No Description	Part No Description	Part No Description	Part No Description	Part No Description													
																										Part No Description	Part No Description	Part No Description	Part No Description	Part No Description	Part No Description	Part No Description	Part No Description															
																									Pari No Description	Part No Description	Part No Description	Part No Description	Part No Description	Part No Description	Part No Description	Part No Description	Part No Description															
																								Part No. Description	Pari No. Description	Part No. Description	Part No. Description	Part No. Description	Part No. Description	Part No. Description	Part No. Description	Part No. Description	Part No. Description															
Dart No Description	Part No. Description	Part No Description	Dart No Description																					— · · · · · · · · · · · · · · · · · · ·	— · · · · · · · · · · · · · · · · · · ·				B 1 11 B 1 11	B																		
Dart No Description	Part No. Description	Part No Description	Dart No Description	Dart No Description	Dort No Decoription																																											
Part No Description	Part No. Description	Part No Description	Dort No Decoription	Dort No Decoription	Dort No Departmention																																											
Part No Description	Part No. Description	Part No Description	Dort No Decoription	Dort No Decoription	Dort No Docorintion	Dort No Docorintion																																										
Part No Description	Part No. Description	Part No Decoription	Part No Decoription	Dort No Departmention	Dort No Departmention	Dout No Deceription																																										

Off-Cut Remover Hektor 2
Contents of delivery:
Hektor 2 with air pressure regulator
Foot switch
Adapter for dust extraction
1 L-blade – Please choose the size



Safe Operation

The PCB is slipped with its milled groove over the blade and is placed onto the matrix. The off-cut is pulled under the blade. When the foot switch is pressed, the off-cut is punched out and the waste material is collected inside the machine.

1	
	Technical data

Technical data	
Separation type	Punch blade
PCB thickness	max. 2.5 mm
Air connection	1/4"-plug-in coupler
Operating pressure	typical 4 bar
Mains voltage	10 - 35° C
Storage/transport temperature	-20 - 50° C
Humidity, non-condensing	10 - 85%
Safety regulations	CE, FCC class A
Weight	2.7 kg
Dimensions H x W x D	170 x 220 x 255 mm





8932145

T-Blade With the T-blade

off-cuts can be punched out right and left of the blade without turning the PCB.

000





Included in delivery.

jammed i	e the blade will no n the PCB, the b st 0.15 mm small pove.	lade should	Width of milled groove	Recomemded blade thickness	Length of blade	Length of cut	Free of compon. on solder side	Length of milled groove	Width of off-cut
	Part No.		Α	В	С	D	Е	F	G
	8932137.001	Blade 1.5 T	≥1.5	1.35	17.2	4.7	>19.0	>19.0	3.0
	8932138.001	Blade 2.0 T	≥2.0	1.85	17.2	5.2	>19.0	>19.0	3.0
	8932191.001	Blade 2.4 T	≥2.4	2.25	18.0	5.7	>19.0	>19.0	3.0
	8932139.001	Blade 2.5 T	≥2.5	2.35	18.0	5.7	>19.0	>19.0	3.0
20	8932144.001	Blade 3.0 T	≥3.0	2.85	18.0	5.7	>19.0	>19.0	2.5
	8932122.001	Blade 1.5 L	≥1.5	1.35	12.0	4.7	>15.0	>13.0	3.0
	8932123.001	Blade 2.0 L	≥2.0	1.85	12.0	5.2	>15.0	>13.0	3.0
	8932141.001	Blade 2.4 L	≥2.4	2.25	12.0	5.7	>15.0	>13.0	3.0
	8932124.001	Blade 2.5 L	≥2.5	2.35	12.0	5.7	>15.0	>13.0	3.0
20	8932125.001	Blade 3.0 L	≥3.0	2.85	12.0	5.7	>15.0	>13.0	2.5
572 	8932171.001 Blades with va thickness on t		are par		F E E	G E C		side of PC compone	